

### ***Push Button Emergency Station***

The palm-size Akuvox E20S Push Button Emergency Station is ruggedized with 316-grade stainless steel. E20S can be used on 1299 and 86 type single in-wall box.



### ***At a Glance***

- Vandal resistant body, with a panic button;
- Linux operation system;
- Two-way audio communication over IP networks with Echo Cancellation feature;
- Flush-mounted;
- Complies with SIP standard;
- For indoor use only;

### **Physical & Power**

- Front panel: 316 grade stainless steel
- Button: 1 call button
- Ethernet port: RJ45, 10/100Mbps adaptive
- Microphone: 1
- Speaker: 1
- 802.3af Power-over-Ethernet
- Size: 100x100x38 mm
- Installation: Flush-mounted
- IK Rating: IK10
- Working Humidity: 10~90%
- Working Temperature: -20°C ~ +55°C
- Storage Temperature: -25°C ~ +60°C
- SIP Protocol: SIP v1 (RFC2543), SIP v2 (RF3261)
- SIP account: 1 SIP account
- Audio codecs: G.711a, G.711μ, G.722
- QoS support: Yes
- Auto Answer support: Yes
- Network mode: DHCP or Static IP
- System time: NTP for auto time setting
- Protocols support: IPv4, HTTP, HTTPS, FTP, DNS, NTP, RTP, TCP, UDP, ICMP, DHCP, ARP